

HP LaserJet Pro M402 Series



A quick, capable printer with robust security and innovative toner for more pages.²

Printing performance and robust security built for how you work. This capable printer finishes jobs faster and delivers comprehensive security to guard against threats.¹ Original HP Toner cartridges with JetIntelligence give you more pages.²



HP LaserJet Pro M402n



HP LaserJet Pro M402dn



HP LaserJet Pro M402dw

Fast printing. Strong protection

- Grab pages and go—without waiting around. This printer wakes up and prints faster than the competition.¹
- Breeze through multipage documents with two-sided printing that's faster than the competition.¹
- Keep printing safe—from boot up to shutdown—with embedded features like LDAP authentication.

More pages, performance, and protection

- Get the most prints for your money—with Original HP High Yield Black Toner cartridges with JetIntelligence.²
- Count on consistent results at high speeds with precision black toner.
- Help ensure you're getting the authentic HP quality you paid for with innovative anti-fraud technology.
- Speed through print jobs right out of the box, using preinstalled toner cartridges. Replace them with optional high-yield cartridges.

Save energy and easily manage tasks

- Help save energy with HP Auto-On/Auto-Off Technology.³
- Print using less energy than competitors—enhanced by Original HP Toner cartridges with JetIntelligence.⁴
- Make the most of your office space, with a printer that conveniently fits right into your work style.
- Easily manage devices and settings using HP Web Jetadmin with a suite of essential management features.⁵

Stay connected with easy mobile printing options


- Easily print from a variety of smartphones and tablets—generally no setup or apps required.⁶
- Easily access, print, and share resources with Ethernet and wireless networking.⁷
- Count on wireless direct printing in the office—from mobile devices—without accessing the company network.⁸
- Help workers print with just a touch of their NFC-enabled mobile device to the printer—no network needed.⁹

¹ Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print speed completed 8/2015. Subject to device settings. Actual results may vary. For details see hp.com/go/Ljclaims ² Based on cartridge yields for HP 80X compared with HP 26X Original HP LaserJet Toner Cartridges. For more information, see hp.com/go/learnaboutsupplies ³ HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; May require a firmware upgrade. ⁴ Based on HP testing using the ENERGY STAR® program's Typical Electricity Consumption (TEC) method or as reported in energystar.gov of top three leading competitors as of 8/2015. Actual results may vary. For details see hp.com/go/Ljclaims ⁵ HP Web Jetadmin is free and available for download at hp.com/go/webjetadmin ⁶ Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at hp.com/go/mobileprinting ⁷ Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections. ⁸ Feature is supported on the HP LaserJet Pro M402dw only. Mobile device needs to be connected directly to the WiFi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Learn more at hp.com/go/businessmobileprinting ⁹ Feature is supported on the HP LaserJet Pro M402dw only. Requires a compatible NFC-printing-enabled mobile device. For a list of compatible NFC-printing-enabled mobile devices, see hp.com/go/nfcprinting

Product walkaround

- 1 2-line LCD control panel
- 2 Front door release button (access to HP JetIntelligence Toner cartridges)
- 3 100-sheet multipurpose tray 1
- 4 250-sheet input tray 2
- 5 150-sheet output bin
- 6 Power on/off button
- 7 Automatic two-sided printing¹
- 8 USB port for job storage with PIN printing²
- 9 Hi-Speed USB 2.0 printing port
- 10 Ethernet port
- 11 Built-in wireless networking³
- 12 Built-in wireless direct printing⁴ and NFC touch-to-print⁵
- 13 Rear door (access to print path)
- 14 Dust cover for tray 2—flips up when legal-size/A4 is loaded

HP LaserJet Pro M402dw shown



Series at a glance



Model	HP LaserJet Pro M402n	HP LaserJet Pro M402dn	HP LaserJet Pro M402dw
Product number	C5F93A	C5F94A	C5F95A
100-sheet multipurpose tray 1, 250-sheet tray 2	✓	✓	✓
550-sheet tray 3	Optional	Optional	Optional
Print speed⁶	Up to 40/38 pages per minute (ppm), letter/A4	Up to 40/38 ppm, letter/A4	Up to 40/38 ppm, letter/A4
Two-sided printing	Manual	Automatic: up to 32/30 images per minute (ipm), letter/A4	Automatic: up to 32/30 ipm, letter/A4
Networking	Built-in 10/100/1000 Base-TX Gigabit Ethernet	Built-in 10/100/1000 Base-TX Gigabit Ethernet	Built-in 10/100/1000 Base-TX Gigabit Ethernet, wireless 802.11b/g/n
Mobile printing	HP ePrint, Apple AirPrint, Mopria-certified Google Cloud Print™ 2.0	HP ePrint, Apple AirPrint, Mopria-certified, Google Cloud Print 2.0	Wireless direct printing, NFC touch-to-print, HP ePrint, Apple AirPrint, Mopria-certified, Google Cloud Print 2.0

¹ Automatic two-sided printing is available on the M402dn and M402dw models only. ² Requires purchase of separate USB flash drive with at least 16 GB capacity. ³ Wireless networking is supported on the M402dw model only. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections. ⁴ Wireless direct is supported on the M402dw only. Mobile device needs to be connected directly to the Wi-Fi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Learn more at hp.com/go/businessmobileprinting ⁵ NFC touch-to-print is supported on the M402dw model only. Requires a compatible NFC-printing-enabled mobile device. For a list of compatible NFC-printing-enabled mobile devices, see hp.com/go/nfcprinting ⁶ Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. For more information, see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

HP Services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs. Choose from:

Optimized Care (optimum performance and stability): 4 hour Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

Standard Care (high level of uptime): Next Business Day Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

Basic Care (minimum recommended support): Next Business Day Onsite Support

4 hr Onsite Support: Onsite support within four hours after a service call received within the coverage window

Next Business Day Onsite Support: Onsite service the next business day after the service call is received

Maintenance Kit Replacement Service: Onsite replacement of your printer's maintenance kit including parts, materials, and labor

Installation with Network Configuration Service: Assembly, network configuration, and basic administrator familiarization

For more information about HP Care Pack, HP Contractual, or HP Managed Print Services, visit hp.com/go/printservices



Windows 8



Top Features

Shift your office into high gear with a powerful printer that doesn't keep you waiting. Print your first page and two-sided prints faster than the competition,¹ and help keep your device, data, and documents safe—from boot up to shutdown.

Print more consistent, high-quality pages than ever before.² Specially designed Original HP Toner cartridges with JetIntelligence deliver better performance, higher energy efficiency, and authentic HP quality—which the competition can't match.²

Take control of printing—and save energy. Use a suite of essential features to help you easily manage this power-conserving printer. It's built to fit right into your office space and work style.

Keep business nimble when needs shift or opportunity strikes—in the office or on the go.³ Print wirelessly with or without accessing the network,^{4,5} and stay connected with Ethernet capabilities. Print with a touch from mobile devices.^{3,6}

Product

C5F93A	HP LaserJet Pro M402n
C5F94A	HP LaserJet Pro M402dn
C5F95A	HP LaserJet Pro M402dw

Accessories

D9P29A	HP LaserJet 550-sheet Feeder/Tray
P0R81AA	HP v222w 16GB Mini USB Drive

Supplies⁹

CF226A	HP 26A Black LaserJet Toner Cartridge (~3,100 pages)
CF226X	HP 26X Black LaserJet Toner Cartridge (~9,000 pages)

HP Care Packs

U8TM2E	HP 3-year Next Business Day LaserJet M402 Hardware Support
U8TM3E	HP 4-year Next Business Day LaserJet M402 Hardware Support
U8TM4E	HP 5-year Next Business Day LaserJet M402 Hardware Support
U8TM7PE	HP 1-year Post Warranty Next Business Day LaserJet M402 Hardware Support

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to hp.com/go/cpc

Paper

Contact HP via phone: Asia: 65 6253 8500

Solutions

HP Web Jetadmin: hp.com/go/wja

HP Universal Print Driver: hp.com/go/upd

HP Imaging and Printing Security Center: hp.com/go/ipsc

¹ Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print speed completed 8/2015. Subject to device settings. Actual results may vary. For details see hp.com/go/Ljclaims

² Based on cartridge yields for HP 80X compared with HP 26X Original HP LaserJet Toner Cartridges. For more information, see hp.com/go/learnabouthsupplies ³ Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at hp.com/go/mobileprinting ⁴ Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections. ⁵ Feature is supported on the HP LaserJet Pro M402dw only. Mobile device needs to be connected directly to the WiFi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Learn more at hp.com/go/businessmobileprinting ⁶ Feature is supported on the HP LaserJet Pro M402dw only. Requires a compatible NFC-printing-enabled mobile device. For a list of compatible NFC-printing-enabled mobile devices, see hp.com/go/nfcprinting

HP LaserJet Pro M402 Series

Technical specifications	HP LaserJet Pro M402n (C5F93A)	HP LaserJet Pro M402dn (C5F94A)	HP LaserJet Pro M402dw (C5F95A)
Functions	Print only		
Print	Automatic (standard)		
Duplex print options	Manual (driver support provided)		Automatic (standard)
Print speed ¹	Black (normal, A4): Up to 38 ppm; Black (normal, letter): Up to 40 ppm; Black Duplex (A4): Up to 30 ipm; Black Duplex (letter): Up to 32 ipm		
First page out ²	Black (A4, ready): As fast as 5.7 sec; As fast as 8.2 sec (100 V); Black (A4, sleep): As fast as 8.1 sec; As fast as 11.1 sec (100 V)		Black (A4, ready): As fast as 6.4 sec; As fast as 9.0 sec (100 V); Black (A4, sleep): As fast as 9.8 sec; As fast as 12.3 sec (100 V)
Print technology	Laser		
Print resolution	Black (best): HP FastRes 1200; Black (fine lines): Up to 1200 x 1200 dpi		
Print resolution technologies	HP FastRes 1200, HP ProRes 1200, 600 dpi		
Print cartridges number	1 (black)		
Standard print languages	HP PCL 5, HP PCL 6, HP postscript level 3 emulation, direct PDF (v 1.7) printing, URF, PCLM, PWG		
Printer management	Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP Web JetAdmin Software; HP Proxy Agent Software; HP Imaging and Printing Security Center; HP Utility (Mac); HP Device Toolbox		
Printer smart software features	Manual duplex, N-up printing, collation, HP ePrint, Apple AirPrint™, Google Cloud, Print Mopria-certified, Instant-on Technology, HP Auto-On/Off technology, JetIntelligence Cartridge Technology, Job Storage with PIN printing	Auto-duplex printing, N-up printing, collation, HP ePrint, Apple AirPrint™, Google Cloud, Print Mopria-certified, Instant-on Technology, HP Auto-On/Off technology, JetIntelligence Cartridge Technology, Job Storage with PIN printing	Auto-duplex printing, N-up printing, collation, HP ePrint, Apple AirPrint™, Google Cloud Print, Mopria-certified, Wireless direct printing, HP Auto Wireless Connect, NFC, Instant-on Technology, HP Auto-On/Off technology, JetIntelligence Cartridge Technology, Job Storage with PIN printing
Connectivity	Standard connectivity		
Standard connectivity	1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network		1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network; 1 Wireless 802.11b/g/n
Mobile print capability ³	HP ePrint, Apple AirPrint™, Mopria-certified, Google Cloud Print 2.0, Mobile Apps		HP ePrint, Apple AirPrint™, Wireless direct printing, Mopria-certified, Google Cloud Print 2.0, Mobile Apps
Network ready	Standard (built-in Gigabit Ethernet)		Standard (built-in Ethernet, Wi-Fi) [Operates as both an AP (with Wi-Fi Direct) and STA]
Network capabilities	Via built-in 10/100/1000Base-TX Ethernet, Gigabit; Auto-crossover Ethernet; Authentication via 802.1X		Via built-in 10/100/1000 Base-TX Ethernet, Gigabit; Auto-crossover Ethernet; Authentication via 802.1X
Wireless Capability	No		Yes, Built-in Wi-Fi; Authentication via WEP, WPA/WPA2, WPA Enterprise; Encryption via AES or TKIP; WPS; Wi-Fi Direct
Memory	Standard/Maximum: 128 MB		
Duty cycle ⁴	Up to 80,000 pages; Recommended monthly page volume: ⁵ 750 to 4,000 pages		
Processor speed	1200 MHz		
Paper handling	Input: 100-sheet tray 1, 250-sheet input tray 2; Optional: third 550-sheet tray		
Output	150-sheet output bin		
Media type	Paper (plain, EcoFFICIENT, light, heavy, bond, coloured, letterhead, preprinted, prepunched, recycled, rough); envelopes; labels; transparencies		
Media weight	Tray 1: 60 to 175 g/m ² ; Tray 2, optional 550-sheet tray 3: 60 to 120 g/m ²		
Media sizes custom	Tray 1: 76.2 x 127 to 215.9 x 355.6 mm; Tray 2, 3: 104.9 x 148.59 to 215.9 x 355.6 mm		
Dimensions (W x D x H)	381 x 357 x 216 mm (15 x 14.06 x 8.5 in)		
Weight	8.58 kg (18.92 lb)		
What's in the box	HP LaserJet Pro M402n; Preinstalled Introductory HP 26A Black LaserJet Toner Cartridge (~1,500 pages); Getting Started Guide; Setup Poster; Support Flyer; Warranty Guide; Printer documentation and software on CD-ROM; Power cord; USB cable	HP LaserJet Pro M402dn; Preinstalled HP 26A Black LaserJet Toner Cartridge (~3,100 pages); Getting Started Guide; Setup Poster; Support Flyer; Warranty Guide; Printer documentation and software on CD-ROM; Power cord; USB cable	HP LaserJet Pro M402dw; Preinstalled HP 26A Black LaserJet Toner Cartridge (~3,100 pages); Getting Started Guide; Setup Poster; Support Flyer; Warranty Guide; Printer documentation and software on CD-ROM; Power cord; USB cable
Warranty features	One-year warranty, return to HP Authorized Service Provider		
Systems	Compatible operating systems		
Compatible operating systems	Windows OS compatible with In-Box Driver: Windows XP SP3 all 32-bit editions (XP Home, XP Pro, etc.), Windows Vista all 32-bit editions (Home Basic, Premium, Professional, etc.), Windows 7 all 32 & 64-bit editions, Windows 8/8.1 all 32 & 64-bit editions (excluding RT OS for Tablets), Windows 10 all 32 & 64-bit editions (excluding RT OS for Tablets); Mac OS (HP Print Drivers available from HP.com and Apple Store): OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite; Mobile OS (In-OS drivers): iOS, Android, Windows 8/8.1/10 RT; Linux OS (In-OS HPLIP); Auto install: BOSS (3.0, 5.0), DEBIAN (6.0, 6.0.1, 6.0.2, 6.0.3, 6.0.4, 6.0.5, 6.0.6, 6.0.7, 6.0.8, 6.0.9, 6.0.10, 7.0, 7.1, 7.2, 7.3, 7.4, 7.5, 7.6), FEDORA (17, 18, 19, 20), LINUX MINT (13, 14, 15, 16, 17), SUSE LINUX (12.2, 12.3, 13.1), UBUNTU (10.04, 11.10, 12.04, 12.10, 13.04, 13.10, 14.04, 14.10); Manual install: MANDRIVA LINUX (2010.0, 2011.0), MEPIS (6.0, 6.5, 7.0, 8.0), PCLINUXOS (2006.0, 2006, 2007.0, 2007, 2008.0, 2008, 2009.0, 2009), RED HAT (8.0, 9.0), RED HAT ENTERPRISE LINUX (5.0, 6.0, 7.0), SLACKWARE LINUX (9.0, 9.1, 10.0, 10.1, 10.2, 11, 12, 12.1), GOS (8.04.1), IGOS (1.0), LINPUS LINUX (9.4, 9.5), LINUX FROM SCRATCH (6); Other OS: UNIX		
Minimum system requirements	PC: Windows 10 (32-bit/64-bit), Windows 8.1 (32-bit/64-bit), Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit): 1 GHz processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Vista (32-bit): 1 GHz 32-bit (x86) processor, 1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Server 2003 (32-bit) (SP1 or greater), Windows Server 2003 R2 (32-bit), Windows Server 2008 (32-bit) (SP1 or greater): 1 GHz 32-bit (x86) processor, 1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Server 2008 (64-bit) (SP1 or greater), Windows Server 2008 R2 (64-bit) (SP1): 1 GHz 64-bit (x64) processor, 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Mac: OS X 10.8 Mountain Lion; OS X 10.9 Mavericks; OS X 10.10 Yosemite; Internet; USB; 1 GB available hard disk space; OS compatible hardware (For OS hardware requirements see apple.com)		
Fonts and typefaces	84 scalable TrueType fonts		
Control panel	2-line backlit LCD graphic display; Buttons (OK, Menu, Cancel, Back); LED indicator lights (Attention, Ready)		2-line backlit LCD graphic display; Buttons (OK, Menu, Cancel, Back, Wi-Fi); LED indicator lights (Attention, Ready, Wi-Fi)
Power	Power supply type: Internal (Built-in) power supply; Power supply required: 110-volt input voltage: 110 to 127 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz); 220-volt input voltage: 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz) (Not dual voltage, power supply varies by part number with #option code identifier); Power consumption: ⁶ 591 watts (Active Printing), 6.1 watts (Ready), 2.8 watts (Sleep), 0.6 watts (Auto-On/Off, via USB connectivity), 0.1 watts (Shutdown or Off)		
Software included	For Windows 7: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Update, HP Device Toolbox, HP Printer Status and Alerts, HP Product Improvement Study, Reconfigure your HP Device; Warranty and Legal Guide, User Guide; For Windows 8+: HP Software Installer/Uninstaller, HP PCL-6 Printer Driver, HP Device Experience (DXP), Warranty and Legal Guide, User Guide, Reconfigure your HP Device; For Windows XP, Windows Vista and associated servers: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, Warranty and Legal Guide, User Guide; For Mac OS: Welcome Screen (Directs users to HP.com or OS App Source for LaserJet Software)		
Acoustic	Acoustic power emissions: ⁷ 6.8 B(A); Acoustic power emissions (ready): Inaudible; Acoustic pressure emissions bystander (active, printing): 54 dB(A); Acoustic pressure emissions bystander (ready): Inaudible		
Environmental ranges	Operating temperature range: 15 to 32.5° C (59 to 90.5° F); Recommended operating temperature: 17.5 to 25° C (63.5 to 77° F); Non-operating humidity range: 10 to 90% RH; Operating humidity range: 10 to 80% RH; Recommended operating humidity range: 30 to 70% RH; Storage Temperature Range: -20 to 40° C (-4 to 104° F)		
Security management	Embedded Web Server: password-protection, secure browsing via SSL/TLS; Network: enable/disable network ports and features, SNMPv1 & SNMPv2 community password change, HP ePrint: HTTPS with certificate validation, HTTP Basic Access Authentication, SASL authentication; Firewall and ACL, SNMPv3, 802.1X, Secure Boot	Embedded Web Server: password-protection, secure browsing via SSL/TLS; Network: enable/disable network ports and features, SNMPv1 & SNMPv2 community password change, HP ePrint: HTTPS with certificate validation, HTTP Basic Access Authentication, SASL authentication; Firewall and ACL, SNMPv3, 802.1X, Secure Boot, authentication via WEP, WPA/WPA2 Personal, WPA2 Enterprise; Encryption via AES or TKIP	
Safety approvals and requirements	IEC 60950-1:2005 +A1:2009+A2:2013/EN 60950-1:2006 +A11:2009+A1:2010+A2:2011+A2:2013; IEC 60825-1:2007/EN 60825-1:2007 (Class 1 Laser/LED Product); IEC 62479:2010/EN 62479:2010; GB4943-2011		
Supported network protocols	TCP/IP, IPv4, IPv6; Print: TCP/IP port 9100 Direct Mode, LPD (raw queue support only), Web Services Printing, HP ePrint, Apple AirPrint™, Google Cloud Print 2.0, Mopria, FTP Print, IPP Print; Discovery: SLP, Bonjour, Web Services Discovery; IP Config: IPv4 (BootP, DHCP, AutoIP, Manual), IPv6 (Stateless Link-Local and via Router, Stateful via DHCPv6), SSL Security and Certificate management; management: SNMPv1, SNMPv2, SNMPv3, HTTP/HTTPS, Syslog, FTP FW Download		

¹ Measured using ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more information see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ² Measured using ISO/IEC 17629. For more information see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ³ Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at hp.com/go/mobileprinting ⁴ Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPS to satisfy the demands of connected individuals or groups. ⁵ HP recommends that the number of pages per month of imaged output be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period. ⁶ Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. ⁷ Acoustic values are subject to change. For current information see hp.com/support. Configuration tested: base model, simplex printing, A4 paper at an average of 38 ppm.

To learn more, visit hp.com

© Copyright 2015 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Microsoft and Windows are registered trademarks of Microsoft Corporation. AirPrint and the AirPrint logo are trademarks of Apple Inc., registered in the U.S. and other countries. Linux is a U.S. registered trademark of Linus Torvalds. UNIX is a registered trademark of The Open Group.

